

Updated July 24, 1996

Models WDA-S260 & WDA-2120

IBM Compatibility Notes

<http://www.storage.ibm.com/hddtech>

Features

- 63/126MB formatted capacity (512 bytes/sector)
- AT standard interface
- Integrated controller
- IBM PC-AT Task File Architecture
- 1:1 interleave
- 1,7 Run-Length Limited (RLL) encoding
- 32KB Read look-ahead buffer
- Self diagnostics on power up
- Automatic retry and data correction on read errors
- No preventative maintenance required
- Media data transfer rate: 15.1 Mbits/Sec
- Closed loop actuator servo (embedded sector servo)
- Rotary voice coil actuator
- Automatic actuator lock
- Dedicated head landing zone
- Average seek time = 18.5 mS (WDA-260)
16.5 mS (WDA-2120)
- All axis (6 directions) mounting permitted
- MTBF 150,000 hours

Performance

	WDA-S260	WDA2120
	-----	-----
Media Read/Write		
Data Transfer--rate		
in Mbits/Sec.	15.1	
Rotational speed	3600 RPM	
Average Latency	8.3mS	
Controller overhead (ave)	1.0mS	
Seek times (in mS)		
Single Track	5.0	5.0
Average Length	18.5	16.5
Full Length	29.5	29.5
Power On to Drive Ready	7 Sec (ave)	
Power Off to Spindle Stop	5 Sec (max)	

Data organization

	WDA-S260	WDA-2120
	-----	-----
Physical layout		
Bytes per Sector	512	512
Total Data Sectors	123552	247104
Total Data Bytes	63,258,624	126,517,248
Sectors per Track	50	50
Sectors per Cylinder	99	198
Spare Sectors per Cylinder	1	2
Numbers of Data Heads	2	4

Numbers of Disks	1	2
Logical layout	WDA-S260	WDA-2120
-----	-----	-----
Logical Heads	8	15
Sectors/Track	17	17
Logical Cylinders	909	969
Data Bytes	63,225,856	126,382,080

DC power requirements

Supply Voltage (single supply)	+5 Volts
Voltage Tolerance (incl. Ripple)	+/-250mV
Ripple (0-20 MHz)	100mVp-p

Power Supply Current (average value in Amps)	Logic	Motor
	-----	-----

WDA-S260

Spin-up	0.13	0.57
Seek	0.31	0.09
Write	0.31	0.09
Read	0.31	0.09
Idle	0.15	0.09
Standby	0.06	-

WDA-2120

Spin-up	0.13	0.71
Seek	0.31	0.09
Write	0.33	0.09
Read	0.33	0.09
Idle	0.15	0.09
Standby	0.06	-

Power consumption

(average value in watts)	WDA-S260	WDA-2120
	-----	-----
Spin-up	3.5	4.2
Seek	2.0	2.0
Write	2.0	2.1
Read	2.0	2.1
Idle	1.2	1.2
Standby	0.3	0.3

Notes:

1. A soft reset is not required to exit 'Standby' mode (the drives can respond to I/F commands while they are in 'Standby').
2. When a 'Sleep' command is issued, the drives go into 'Standby' mode which allows a faster response than from 'Sleep' mode.

Electrical interface

Drive address:

PIN	Signal	I/O	PIN	Signal	I/O
01	-HRESET	I	02	GND	
03	HD07	I/O	04	HD08	I/O
05	HD06	I/O	06	HD09	I/O
07	HD05	I/O	08	HD10	I/O
09	HD04	I/O	10	HD11	I/O
11	HD03	I/O	12	HD12	I/O
13	HD02	I/O	14	HD13	I/O
15	HD01	I/O	16	HD14	I/O
17	HD00	I/O	18	HD15	I/O
19	GND		(20)	Key	
21	(Resv)		22	GND	
23	-HIOW	I	24	GND	
25	-HIOR	I	26	GND	
27	IORDY	O	28	(Resv)	
29	(Resv)		30	GND	
31	HIRQ	O	32	-HIOCS16	O
33	HA01	I	34	-PDIAG	I/O
35	HA00	I	36	HA02	I
37	-HCS0	I	38	-HCS1	I
39	-DASP	I/O	40	GND	
41	+5V Logic		42	+5V Master	
43	GND		44	-XT/AT	I

Note:

"O" designates an output from the Drive.
 "I" designates an input to the Drive.
 "I/O" designates an input/output common.
 "PWR" designates a power supply to the Drive.
 "(Resv)" designates reserved pins and all of these
 have to be left unconnected.

Note:

There are two input pins for the +5 Volt supply, the '+5V LOGIC' line is connected to the internal logic circuits and the '+5V MOTOR' line connects to the spindle motor and associated drivers. This allows the user to reduce power consumption by switching the '+5V LOGIC' supply on and off. The '+5V MOTOR' line should be connected directly into the system power supply to minimize voltage drop caused during motor spin-up, etc.

If this power management option is applied, all signal lines that will be electrically active in the host system while the Drive is disconnected from 5 volt logic supply must be isolated through "TRI-STATE" drivers.

For normal installation of these drives, connect the '+5V LOGIC' and '+5V MOTOR' lines together.

Command description

The following Commands are supported by the Drive:

Commands	(HEX)
-----	-----

Check Power Mode	(E5)
Execute Drive Diagnostics	(90)
Format Track	(50)
Identify Drive	(EC)
Idle	(E3)
Idle Immediate	(E1)
Initialize Drive Parameters	(91)
Read Buffer	(E4)
Read Long (retry)	(22)
Read Long (no retry)	(23)
Read Multiple	(C4)
Read Sectors (retry)	(20)
Read Sectors (no retry)	(21)
Read Verify Sectors (retry)	(40)
Read Verify Sectors (no retry)	(41)
Recalibrate	(1X)
Seek	(7X)
Set Features	(EF)
Set Multiple	(C6)
Sleep	(E6)
Standby	(E2)
Standby Immediate	(EO)
Write Buffer	(E8)
Write Long (retry)	(32)
Write Long (no retry)	(33)
Write Multiple	(C5)
Write Sectors (retry)	(30)
Write Sectors (no retry)	(31)
Write Verify	(3C)

Operating environment

Humidity:

Operating Relative	8% to 90% noncondensing
Nonoperating Relative	5% to 95% noncondensing

Wet bulb temperature:

Maximum Wet Bulb:

Operating	29.4 degrees Centigrade noncondensing
Nonoperating	35.0 degrees Centigrade noncondensing

Elevation:

Operating Altitude	-100 to 3000m
Ship/Storage Altitude	-300 to 12000m

Temperature:

Operating	5 to 55 degrees Centigrade
Storage	-40 to 65 degrees Centigrade
Shipping	-40 to 65 degrees Centigrade
Temperature Gradient	15 degrees Centigrade per hour (maximum)
(Operating, Storage and Shipping)	

Air cooling requirement

The host system must provide sufficient air flow across the drive to

maintain the temperature at less than 60 degrees Centigrade (measured at the center of the drives' top cover).

Operating and nonoperating vibration

Due to the complexity of this subject, we recommend that users contact the Distributor to discuss how to perform the necessary measurements if they believe this to be an area which requires evaluation.

Operating shock

The drive will withstand (with no hard error) a 10G half-sine wave shock pulse of 11mS duration.

Nonoperating shock

The drive will withstand (with no permanent damage or degradation in performance) a 100G half-sine wave shock pulse of 11mS duration.

Mechanical data

Dimensions	WDA-S260	WDA-2120
Height	12.7 +0.35mm -0.3mm	17.0 +0.35mm -0.3mm
Width	70+/-0.25mm	70+/-0.25mm
Depth	100+/-0.25mm	100+/-0.25mm
Weight	140g maximum	180g maximum



Questions regarding IBM's warrant terms or methodology used to derive this data should be referred to your IBM OEM representative. Data subject to change without notice.

AMP is a trademark of AMP Incorporated.

DATA MATE is a trademark of AMP Incorporated.

MOLEX is a trademark of Molex Incorporated.

NEXT is a trademark of NEXT Corporation.

Western Digital is a trademark of the Western Digital Corporation.